



ClareOne Keyfob

CLR-C1-KF



The ClareOne Keyfob is a battery operated wireless handheld control and panic device. This keyfob can be used to arm/disarm the ClareOne panel or to activate a panic alarm by pressing the SOS button.

Specifications

Compatible panel	ClareOne (CLR-C1-PNL1)
Transmitter frequency	433MHz
Encrypted	Yes
Transmitted indications	Low battery
Buttons	4 Buttons: Stay, Away, Disarm, SOS
LED indication	1 LED (blue)
Battery type	CR2032
Battery life	5 years
Operating temperature	32 to 122.6°F (0 to 50°C)
Relative humidity	85% max
Dimensions (W x H x D)	1.49 x 2.53 x .55 in. (38 x 64.5 x 14 mm)
Water resistant	IPX4
Certifications	FCC: 15.109 Class B 15.231, Industry Canada: ICES-003, RSS-210, ETL listed to: UL-1023 and ULC-C1023

*The ClareOne Keyfob must be within range of the ClareOne panel to function properly.

- Can be attached to any key ring
- Arm away
- Arm stay
- Disarm security
- Panic
- Long lasting battery life
- Pairs easily and quickly with the ClareOne panel

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, wireless security, controllable lighting, and IP CCTV components. For more information, visit clarecontrols.com.