

Document: OP500
Type: Procedure details
CM version: CM4-CM6

Saving option changes on OP500

I. Making option changes

- Step 1: Plug in OP500 to control module
- Step 2: Make initial changes to control module
- Step 3: Write changes

II. Saving option changes

- Step 1: Tap the “W” button 1 time
- Step 2: Using left arrow button, select a file that you want to save to FL-1 through FL-5
- Step 3: Tap “W” button again to save it to the desired file *

*Make sure the file name shows up (on the bottom row of the OP 500 LCD text) with the same number that you get when initially plugged in. The number will be different for the different control modules

- i. 180-CM4000
- ii. 181-CM4200dx
- iii. 182-CM4300
- iv. 183-CM6200
- v. 184-CM5200
- vi. 185-CM6000
- vii. 186-CM5000

For additional questions call 888-820-3690 ext: 203

Document: OP500
Type: Procedure details
CM version: CM4-CM6

TIP 002

Writing saved option changes

I. Programming new control module using FL

- Step 1:** Plug OP500 into control module
- Step 2:** After link is established tap the “*R*” button 1 time
- Step 3:** Select file you want to load onto the control module according to the control module you’re using
- Step 4:** You should see “open” flashing on the bottom line of text tap the “*R*” button 1 time to open the file.
- Step 5:** Press and hold the “*W*” button to write the changes to the control module that have been saved in the file you’ve selected
- Step 6:** Once you get the success message you are finished

* You will need to save a file for each control module model number you will be working with as listed above. These files are hard written into the programmer so you will not lose the information unless you write over the files.

For additional questions call 888-820-3690

ext: 203